



KMA-8360

Mixer Amplifier with MP3/FM Tuner/Bluetooth

| | | |
|---------------------------------|--|---|
| Rated output power | | 350W |
| Output | Low impedance | 4-16 Ω |
| | 70V | 14 Ω |
| | 100V | 28 Ω |
| AUX output level | | 0.775V (0dBV) |
| Single Zone Output | | 100V |
| Input level | MIC 1,2,3 | 600 Ω , 10-15mV (unbalanced) |
| | AUX 1,2 | 10K Ω , 200-470mV (unbalanced) |
| Extra Input | | SD slot, USB slot, RCA connector |
| Frequency response | | 60Hz-15KHz (\pm 3dB) |
| T.H.D. | | <0.5% at 1KHz, 1/3 rated output power |
| S/N ratio | MIC 1,2,3 | \geq 72dB |
| | AUX 1,2 | \geq 85dB |
| Tone | Bass | \pm 10dB at 100Hz |
| | Treble | \pm 10dB at 12KHz |
| Muting Function | | MIC1 overrides other input signals at 0~30dB |
| Controls | | Volume, tone/treble, mute, power |
| Protection | AC fuse, Overload, Short circuit, high temperature | |
| | FUUSE \times 6A | |
| Cooling Fan | | DC 12V FAN |
| LED indicator | | AC: POWER, level: 2、4、6、8、10 |
| Power supply | | AC220~240V, 50-60Hz |
| Power consumption | | 485W |
| Power cord | | (3 \times 0.75 mm ²) \times 1.5M (standard) |
| Product dimension (mm) | | 89(H) \times 483(W) \times 366(D) |
| Packaging dimension (mm) | | 185(H) \times 520(W) \times 435(D) |
| Net weight (kg) | | 14.5 |
| Packaging weight (kg) | | 15.80 |