



# KMA-8500

Mixer Amplifier with MP3/FM Tuner/Bluetooth

<b>Rated output power</b>		500W
<b>Output</b>	<b>Low impedance</b>	4-16Ω
	<b>70V</b>	10Ω
	<b>100V</b>	20Ω
<b>AUX output level</b>		0.775V (0dBV)
<b>Single Zone Output</b>		100V
<b>Input level</b>	<b>MIC 1,2,3</b>	600Ω, 10-15mV (unbalanced)
	<b>AUX 1,2</b>	10KΩ, 200-470mV (unbalanced)
<b>Extra Input</b>		SD slot, USB slot, RCA connector
<b>Frequency response</b>		60Hz-15KHz (±3dB)
<b>T.H.D.</b>		<0.5% at 1KHz, 1/3 rated output power
<b>S/N ratio</b>	<b>MIC 1,2,3</b>	≥72dB
	<b>AUX 1,2</b>	≥85dB
<b>Tone</b>	<b>Bass</b>	±10dB at 100Hz
	<b>Treble</b>	±10dB at 12KHz
<b>Muting Function</b>		MIC1 overrides other input signals at 0~30dB
<b>Controls</b>		Volume, tone/treble, mute, power
<b>Protection</b>	AC fuse, Overload, Short circuit, high temperature	
	FUSE×8A	
<b>Cooling Fan</b>		DC 12V FAN
<b>LED indicator</b>		AC: POWER, level: 2、4、6、8、10
<b>Power supply</b>		AC220~240V, 50-60Hz
<b>Power consumption</b>		675W
<b>Power cord</b>		(3×0.75 mm <sup>2</sup> )×1.5M (standard)
<b>Product dimension (mm)</b>		89(H)×483(W)×366(D)
<b>Packaging dimension (mm)</b>		185(H)×520(W)×435(D)
<b>Net weight (kg)</b>		15.5
<b>Packaging weight (kg)</b>		17.20