



kasper



KMA-8240

Mixer Amplifier with MP3/FM Tuner/Bluetooth

Rated output power		240W
Output	Low impedance	4-16Ω
	70V	19Ω
	100V	39Ω
AUX output level		0.775V (0dBV)
Single Zone Output		100V
Input level	MIC 1,2,3	600Ω, 10-15mV (unbalanced)
	AUX 1,2	10KΩ, 200-470mV (unbalanced)
Extra Input		SD slot, USB slot, RCA connector
Frequency response		60Hz-15KHz (±3dB)
T.H.D.		<0.5% at 1KHz, 1/3 rated output power
S/N ratio	MIC 1,2,3	≥72dB
	AUX 1,2	≥85dB
Tone	Bass	±10dB at 100Hz
	Treble	±10dB at 12KHz
Muting Function		MIC1 overrides other input signals at 0~30dB
Controls		Volume, tone/treble, mute, power
Protection	AC fuse, Overload, Short circuit, high temperature	
	FUSE×6A	
Cooling Fan		DC 12V FAN
LED indicator		AC: POWER, level: 2、4、6、8、10
Power supply		AC220~240V, 50-60Hz
Power consumption		350W
Power cord		(3×0.75 mm ²)×1.5M (standard)
Product dimension (mm)		89(H)×483(W)×366(D)
Packaging dimension (mm)		185(H)×520(W)×435(D)
Net weight (kg)		13.8
Packaging weight (kg)		15.40